

Service Document **Exchange Set**

City Boy 52

**Service
Manual**

**Sicherheit
Safety**

Materialnr./Part No.
720108000000



Es gelten die Vorschriften und Sicherheitshinweise gemäß dem Service Manual "Sicherheit", Materialnummer 720108000000, sowie zusätzlich die eventuell abweichenden, landesspezifischen Vorschriften!



The regulations and safety instructions shall be valid as provided by the "Safety" Service Manual, part number 720108000000, as well as the respective national deviations.

Dieses Service Dokument ist nur in Datenform verfügbar

This Service Document is only available as data

Änderungen vorbehalten/Subject to alteration

Made by GRUNDIG in Germany • E-BS-SA 0501

<http://www.grundig.com>

SOLAR ELECTRONICS CORP. LTD			
Model :	CB-52	Date : 7NOV2000	
Brand :	GRUNDIG	Prepared By : C.S.Heung	
Step Frequency :	50KHz	Approved By : CS.HEUNG	
Step No.	Frequency Setting	Alignment Location	Preset Memory
		Equipment Connection	
1	IF 10.7MHz	FM IF Marker Generator Output Connect To TP3,TP2 Gnd. Input Connect To TP4, TP5 Gnd.	M5
2	87.5MHz	Digital Volt Meter Connect To TP6,TP5 Gnd	M1
3	108MHz	Digital Volt Meter Connect To TP6,TP5 Gnd	M5
4	90.1MHz	FM Sweep Marker Generator Output Connect To TP1,TP2 Gnd Input Connect To TP4,TP5 Gnd.	M2
5	106.1MHz	Same As Step 4.	M4
		Repeat Step 4,5 Until No Tracking Error Occure	
6	98.1MHz	Same As Step 4.	M3
7	87.5MHz	Same As Step 4.	M1
8	108MHz	Same As Step 4.	M5

FM







