

TC-765

UK Model
AEP Model
US Model
Canadian Model
PX Model



STEREO TAPE DECK

SPECIFICATIONS

GENERAL

Power Requirements:	120V ac, 60 Hz (US, Canadian model) 110V, 120V, 220V, 240V ac, 50/60 Hz (UK, AEP, PX model)	Fast Forward and Rewind Time:	Approx. 150 seconds with 740 m (2,400 ft) tape
Power Consumption:	110W (US, Canadian model) 90W (UK, AEP model) 80W (PX model)	Recording Time:	With 1,100 m (3,600 ft), 27 cm reel Stereo recording 180 minutes at 19 cm/s Mono recording 720 minutes at 9.5 cm/s
AC Outlet:	300W, unswitched (US, Canadian model)	Heads:	Record head 1, Playback head 1 Erase head 1
Dimensions:	Approx. 445 (w) x 525 (h) x 235 (d) mm 17½ (w) x 20⅝ (h) x 9¼ (d) inches including projecting parts and controls	Motors:	AC servo-controlled capstan motor 1 Induction reel motor 2
Weight:	26.5 kg, 58 lb 7 oz (US, Canadian model) 27 kg, 58 lb 8 oz (UK, AEP, PX model)	Reel:	Up to 27 cm (10½-inch)
Track:	4-track 2-channel stereo recording and playback		
Tape Speed:	19 cm/s (7½ ips) 9.5 cm/s (3¾ ips)		

— Continued on page 2 —

SAFETY-RELATED COMPONENT IDENTIFICATION

COMPONENTS IDENTIFIED BY SHADING IN THE SCHEMATIC DIAGRAMS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY.

SONY
SERVICE MANUAL

TC-765

Frequency Response: With Sony Ferri-Chrome tape
 30–25,000 Hz \pm 3 dB at 19 cm/s
 30–18,000 Hz \pm 3 dB at 9.5 cm/s
 With SLH tape
 30–25,000 Hz \pm 3 dB at 19 cm/s
 30–18,000 Hz \pm 3 dB at 9.5 cm/s
 With regular tape
 30–18,000 Hz \pm 3 dB at 19 cm/s
 30–15,000 Hz \pm 3 dB at 9.5 cm/s

Wow and Flutter: NAB
 0.04% WRMS at 19 cm/s
 0.08% WRMS at 9.5 cm/s
 DIN
 \pm 0.07% at 19 cm/s
 \pm 0.15% at 9.5 cm/s

S/N Ratio: 61 dB (NAB) with Sony Ferri-Chrome Tape
 61 dB (DIN 1975 rev.) with Sony Ferri-Chrome Tape
 56 dB (DIN, old)

Total Harmonic Distortion: 0.7%

Bias Frequency: 160 kHz

Equalization: 3,180 μ S + 50 μ S (19 cm/s)
 3,180 μ S + 90 μ S (9.5 cm/s)

Inputs: MIC (two phone jacks)
 Sensitivity: 0.2 mV (-72 dB)
 Impedance: for low-impedance microphone
 LINE IN (two phono jacks)
 Sensitivity: 0.06 V (-22 dB)
 Impedance: 100 k Ω
 REC/PB (connector) (UK, AEP, PX model)
 Input impedance: less than 10 k Ω

Outputs: LINE OUT (two phono jacks)
 Normal level: 0.435 V (-5 dB) with PB LEVEL control set to center detent position
 0.775 V (0 dB) with PB LEVEL control set to "10"
 Load impedance: 100 k Ω
 Suitable load impedance: more than 10 k Ω
 HEADPHONES (binaural jack)
 Load impedance: for low-impedance headphones
 REC/PB (connector) (UK, AEP, PX model)
 Output impedance: less than 10 k Ω

Other Jack: 11-pin remote control connector

0 dB = 0.775 V

MODEL IDENTIFICATION Specification label

UK, AEP model

SONY.	
TAPECORDER	TC-765
110.120.220.240V	\sim 50/60Hz 90W
NO. <input type="text"/>	
MADE IN JAPAN	

US model

SONY.	
TAPECORDER	TC-765
AC 120V	60Hz 110W
NO. <input type="text"/>	
MADE IN JAPAN	

Canadian model


SONY.	
TAPECORDER	TC-765
AC 120V	60Hz 110W
NO. <input type="text"/>	
MADE IN JAPAN	

PX model

SONY.	
TAPECORDER	TC-765
NO. <input type="text"/> MADE IN JAPAN	
AC 120V 80W 50/60Hz	


SECTION 1
OUTLINE

1-1. BLOCK DIAGRAM - System Control Section -



TC-765 TC-765

1-2. BLOCK DIAGRAM – Amplifier Section –



SECTION 2
DISASSEMBLY

1-3. NOTE ON REPAIRING

NOTE ON REPAIRING

- This set does not change playback level when TAPE SELECT switches are changed.
- The LINE OUT signal is cut when REC MONITOR MUTE switch (S607) on the rear panel is turned ON except when MONITOR switch is in TAPE position in playback mode.
- If TIMER switch is previously set to ON position, it may happen to erase test tapes because the set becomes automatically in the auto playback (awakening) or auto record mode determined by REC MODE switch position when POWER switch is turned ON.
- PB LEVEL controls on the front panel control LINE OUT and HEADPHONES levels, and also VU meters indicate the amount of PB LEVEL controlling. When PB LEVEL is in the center-click positions, LINE OUT levels are standard 0.44V (-5 dB) and VU meters indicate "0". When PB LEVEL controls are in their full-clockwise stops, LINE OUT levels are 0.775V (0 dB).
- Three kinds of hexagonal-socket screwdrivers are needed for the following adjustment/removal.


Screwdriver	Adjustment/removal
1.27 mm	Tension-arm pin Intermediate pin Switch knob Switch lever
1.5 mm	Head azimuth FG-holding boss Control knob Motor pulley
2.0 mm	Reel drum

6. Tape BIAS/EQ recommendations

The following list shows the recommended settings, which have been determined through critical listening tests and electrical characteristic measurements on commercially available tapes. The setting can be changed according to the personal preference. For Sony tapes, be sure to use the recommended settings to obtain the optimum tape characteristics.

EQ	NORMAL	SPECIAL	Fe-Cr
BIAS			
LOW	SONY PR	BASF LH, LHS AGFA PE, PEM MEMOREX	SCOTCH #211, #212, #213 AMPEX 406, 407
MED	SCOTCH #218	SONY SLH SCOTCH CLASSIC TDK AUDUA	SONY DUAD SCOTCH #206, #207 MAXELL UD
HIGH			SCOTCH #250



- | | | |
|------------------------------------|---------------|--|
| Reel Panel Removal: | ①, ② | (to Mechanical Adjustment) |
| Amp Panel Removal: | ③, ④, ⑤, ⑥, ⑦ | (to VU Meter and Variable Resistor Replacement) |
| Perforated Panel (top) Removal: | ⑧, ⑨ | (to Fuse Replacement) |
| Perforated Panel (bottom) Removal: | ⑩, ⑪ | (to Audio Amp Board Check) |
| Side Board (right) Removal: | ⑫, ⑬ | (to Tape Speed and Forward Torque Adjustments) |
| Side Board (left) Removal: | ⑭, ⑮ | (to B+ and Supply Reel Back Tension Adjustments) |
| Rear Board Removal: | ⑯, ⑰ | (to System Control Board Checking) |




TENSION ARM BASE REMOVAL

Microswitch Installation


Turn the tension lever and adjust the position of the microswitch for the specified clearance when it switches.



REEL TABLE REMOVAL




HEAD COVER REMOVAL





Note: When reattaching the pinch rollers, be sure to reattach the one with "1" mark at the right side.

MOTOR PULLEY INSTALLATION

Use a hexagonal screwdriver.



ELECTROSTATIC DISCHARGE BRUSH INSTALLATION




SECTION 3
MECHANICAL ADJUSTMENT

3-1. MECHANICAL ADJUSTMENTS


Tape Path Adjustment

1. In playback mode, travel a blank tape SLH-S1, and adjust the positions of the tension-arm guide and intermediate pin.




After the adjustment, tighten the adjustment screws.

2. Travel a blank tape SLH7-740 and adjust the position of the tape guides to eliminate tape curls.



3. Travel a blank tape SLH-S1 and adjust the height of each head for the specified clearances. To adjust the erase head height, select appropriate spacer. To adjust the record and playback heads, turn the height/zenith adjustment screws in the same angle and direction.





After the adjustment, apply a suitable locking compound to the adjusted screws.

Reel Table Height Adjustment


— playback and rewind modes —

1. Loosen the adjustment screws and adjust the height of the reel tables for the specified height.
2. If the tape touches the reel in playback, fast forward and rewind modes, recheck the tension arms, standard reels and the tape.

Tape should travel in the center of this width.




Note: Adjustment screw positions for the 2T PB and 4T PB heads are the same as the 2T REC head. Azimuth adjustment screws are so constructed to react each other. Take care in adjusting azimuth adjustment screw.



Brake Adjustment (1)

Adjust both the supply- and take-up-side brakes.

1. In stop mode, 0.5–0.7 mm clearance should exist between the brake-band guide and brake band.
2. In playback mode (the brake solenoid should be in ON condition), loosen the adjustment screw and adjust the position of the solenoid link in the arrowed direction so that the brake band and brake-band guide uniformly touch.




Note: If the brake-release stroke is long, the brake band may bend at the position shown with *. Be sure not to bend the brake band.

3. After the adjustment, apply a suitable locking compound to the adjustment screw.

Pinch Roller Lever Position Adjustment

1. Remove the head cover.
2. Reattach both the pinch rollers.
3. Place the set in the playback mode. Check that the solenoid is in on condition (energized).
4. Loosen the adjustment screw and push the slide adjustment plate in the arrowed direction for the specified clearance between the pinch roller levers A and B, and tighten the adjustment screw.
5. After the adjustment, apply a suitable locking compound to the adjustment screw.




Brake Adjustment (2) and Brake Torque Adjustment

Adjust both the supply- and take-up-side brakes.

1. In stop mode, loosen the adjustment screw and adjust the position of the brake stopper for the specified clearance between the brake stopper and brake lever.
2. After the adjustment, tighten the adjustment screw and apply a suitable locking compound to the screw.
3. Measure both the forward and backward brake torques. Adjust spring-hook position for the specified torques.


backward torque: 1,800–2,500 g·cm (25–34 oz·inch)
forward torque: 600–700 g·cm (8.5–9.5 oz·inch)





Pinch Roller Pressure Check

— playback mode —

1. Place the dial-cord ring between the pinch roller and pinch-roller cap.




2. In playback mode, pull the spring scale on the center line made by the centers of the capstan and pinch roller.
3. Slowly return the pinch roller and read the spring scale just when the pinch roller starts to rotate.



Forward Torque Adjustment

1. Remove the side board (right).
2. Apply the rated ac voltage to the AC IN.
3. Set the TAPE SPEED switch to 19 cm/s and REEL SIZE switch to 10½.
4. In playback mode, adjust RV703 for the specified torques.
5. Set REEL SIZE switch to 7 and check torques.

	REEL SIZE switch	
	10½	7
50 Hz	520-580 g-cm (7.3-8.0 oz-inch)	260-320 g-cm (3.6-4.4 oz-inch)
60 Hz	380-440 g-cm (5.3-6.1 oz-inch)	180-240 g-cm (2.5-3.3 oz-inch)



Supply Reel Back Tension Adjustment


Note: This adjustment requires a ultra-low frequency audio signal generator. If the signal generator is not available, do not attempt this adjustment.

1. Remove the side board (left).
2. Apply the rated ac voltage to AC IN.
3. Set RV702 to the fully-counterclockwise stop.
4. Put a torque meter on the supply reel tape.
5. Unsolder the RED and WHT lead wires from the FG at the system control board.
6. Set the signal generator's frequency to 20.2 Hz and attenuator to -20 dB.
7. Connect the signal generator to the points from where the two lead wires are unsoldered in step 5.
8. Set REEL SIZE switch to 10½ and TAPE SPEED switch to 19 cm.
9. In playback mode, adjust RV702 for specified torque.

	<i>Back tension torque</i>
50 Hz	150 g-cm (2.1 oz-inch)
60 Hz	120 g-cm (1.65 oz-inch)


10. Change the audio signal generator's frequency to 7.14 Hz and check the torque meter reeding.

	<i>Torque meter reeding</i>
50 Hz	280-340 g-cm (3.9-4.7 oz-inch)
60 Hz	220-280 g-cm (3.1-3.8 oz-inch)



Fast Forward and Rewind Back Tension Check

1. Apply the rated ac voltage to AC IN.
2. Turn either the left- or right-side tension arm on using a rubber band.
3. Put a torque meter on the supply reel table. In fast forward mode, pull the torque meter in the arrowed direction at a speed of 19-9.5 cm/s and read the fast forward back tension on the torque meter.
4. Put a torque meter on the take-up reel table. In rewind mode, pull the torque meter and read the rewind back tension as in step 3.



	<i>REEL SIZE switch</i>	
	10½	7
50 Hz	110-150 g-cm (1.6-2.0 oz-inch)	80-120 g-cm (1.15-1.6 oz-inch)
60 Hz	70-110 g-cm (1.0-1.5 oz-inch)	50-90 g-cm (0.7-1.2 oz-inch)

3-2. SYSTEM CONTROL CHECK

System Control Check

Setting:

REEL SIZE switch: 10½
 TAPE SPEED switch: 19 cm
 TIMER switch: OFF
 MONITOR switch: TAPE
 PB LEVEL control: center click
 REC MONITOR MUTE switch: OFF
 INPUT SELECT switch: LINE
 (AEP, UK, PX model)
 REC MODE switches: released positions

Put the 10½-inch blank tapes on the set.

Checking:


1. Turn POWER switch ON. The VU meter lamps should light up.
2. Depress REC MODE switches. The L-side lamp should light up when the L-side REC MODE switch is depressed, and the R-side lamp should light up when the R-side REC MODE switch is depressed. And the record button lamp should put on and off repeatedly.
3. Depress the pause button. The pause button lamp should light up.
4. Depress the record and forward buttons simultaneously. The record button lamp should turn from flickering to ON. At the same time, the forward button lamp should light up.
5. Press the pause button. The pause button lamp should turn off and the pinch roller should press the capstan and become in forward record mode.
6. Depress the fast forward button. The set should become in the fast forward mode. In this mode, the record button lamp flickers, forward button lamp turns off and the fast forward button lamp turns on.
7. Depress the rewind button. The set should become in the rewind mode. In this mode, the fast forward button lamp should turn off and rewind button lamp turns on.
8. Depress the forward button. The rewind button lamp should turn off and forward button lamp turns on. The tape should once completely stop traveling, and then become in the forward mode.
9. The set should become in the stop mode only when both the tension arm microswitches turn off. The set should not become in the stop mode when one of the tension arm microswitches turns off.
10. Turn TIMER switch ON. Turn POWER switch OFF once, and two to three second later turn POWER switch ON. Now the set should become in the forward record mode automatically.
11. With REC MODE switches released (i.e., in the playback positions), perform the same procedure as shown in step 10. The set should become in forward mode automatically.
12. Place the set in the forward record and simultaneous monitoring mode. Turn REC MONITOR MUTE switch on the rear panel ON. Now the signal should not come out from LINE OUT jacks.
 Rewind the recorded portion of the tape and place the set in the forward mode. Now the signal should come out from LINE OUT jacks. Turn REC MONITOR MUTE switch OFF.
13. Depress the forward and pause buttons. Move the recorded portion of the tape back and forth. Sound signal should come out from LINE OUT jacks.

3-3. ELECTRICAL ADJUSTMENTS

Note: The adjustments should be performed in the order given in this service manual. The adjustments should be performed for both L-CH and R-CH.

Standard Record:

Set the REC LEVEL control for the specified output level.



Control and Switch Settings:

Unless otherwise specified, set the controls and switches as follows.




Controls	In playback	In record
MIC REC VOL	/	The position to produce the rated LINE OUT level with rated MIC input level.
LINE REC VOL		The position to produce the rated LINE OUT level with rated LINE IN level.
PB VOL	center click	center click

Switch	In playback	In record
POWER	ON	ON
REEL SIZE	7	7
TAPE SPEED	19	19
TIMER	OFF	OFF
MIC ATT	/	0
TAPE SELECT (BIAS)	/	MED
TAPE SELECT (EQ)	/	SPECIAL
REC MODE	PB	REC
MONITOR	TAPE	SOURCE (TAPE)
REC MONITOR MUTE	OFF	OFF
INPUT SELECT (AEP, UK, PX model)	LINE	LINE

B+ Voltage Adjustment

Adjustment Location:


— function button board —



Tape Speed Adjustment

Procedure:

Mode: playback



Use a non-metallic screwdriver. Adjust RV901 (19 cm/s) and RV902 (9.5 cm/s) for 0% checker or 4,000 Hz (19 cm/s) and 2,000 Hz (9.5 cm/s) counter readings.

Specification:


Speed checker	Frequency counter
$\pm 0.75\%$	3,970–4,030 Hz (19 cm/s) 1,985–2,015 Hz (9.5 cm/s)

Frequency difference between beginning and end of tape:

19 cm/s: within 0.5% or 20 Hz

9.5 cm/s: within 0.5% or 10 Hz

Adjustment Location:




Playback Head Angle Adjustment

Procedure:

Mode: playback

SONY J-19-F2
(4th tone, 12.5 kHz, -10 dB)



Loosen the adjustment screws ① and ② and adjust the position of the PB head by moving the screw ② in the arrowed direction for the highest VTVM reading.


After the adjustment, apply a locking compound to the screws.

Note: Slightly touch the supply reel and at this time the VTVM reading deviation should be less than 1 dB.

Adjustment Location:

— head base —

angle adjustment screw ②




angle adjustment screw ①

Playback Head Azimuth and Phase Adjustment

Procedure:

1. Mode: playback

SONY J-19-F2
(4th tone, 12.5 kHz, -10 dB)




Turn the adjustment screws of the PB head for the highest VTVM reading. If the highest peaks for L and R do not coincide, place the adjustment screw to the point where both L and R outputs are same and within 1 dB from the peaks.

Note: The two adjustment screws are so constructed to react each other. When one side screw is loosened, tighten another screw in the same angle.

2. Mode: playback

SONY J-19-F2
(4th tone, 12.5 kHz, -10 dB)




Adjust	On the oscilloscope			
azimuth adjustment screw				
	in-phase	30°	90°	more than 90°
	good			wrong

Note: Difference between the highest levels of L and R and the finally adjusted level should be within 1 dB.

Adjustment Location:

— head base —




azimuth adjustment screws
(hexagonal socket \square 1.5 mm)

Playback Frequency Response Adjustment

Procedure:

Mode: playback
PLAYBACK HEAD switch: 2 TRACK

SONY J-19-F2
(2nd tone, 400 Hz, -10 dB)
(3rd tone, 10 kHz, -10 dB)
(4th tone, 12.5 kHz, -10 dB)




Adjust the pattern connections to obtain the specified values.

Playback	Level difference from 400 Hz
10 kHz 12.5 kHz	within ± 2 dB

Adjustment Location:

— audio amp board —



pattern connection pattern connection


Note: After this adjustment perform the playback level adjustment.

Playback Level Adjustment

Procedure:

Mode: playback

SONY J-19-F2
(1st tone, 400 Hz, 0 dB)




Adjust	VTVM reading
RV104 (L-CH)	0.44 V (-5 dB)
RV304 (R-CH)	allowance: ± 1 dB (0.39–0.49 V)

Note: Level difference between L and R channels should be within 1 dB.

Adjustment Location:

— audio amp board —

RV104 (L-CH) RV304 (R-CH)




VU Meter Calibration

Setting:

MONITOR switch: SOURCE

Procedure:

1. Mode: record




2.

Adjust	VU meter indication
RV106 (L-CH)	"0"
RV306 (R-CH)	

Adjustment Location:

— audio amp board —



RV106 (L-CH)

RV306 (R-CH)



Record Head Angle Adjustment

Setting:

MONITOR switch: TAPE

Procedure:

Mode: record and simultaneous playback
PLAYBACK HEAD switch: 2T REC



Loosen the adjustment screws ① and ②. Correctly position the record head by moving the adjustment screw ② in the arrowed directions for the highest VTVM reading.


Note: Slightly touch the supply reel and at this time the VTVM reading deviation should be less than 1 dB.

After the adjustment, apply a suitable locking compound to the screws.

Adjustment Location:

— head base —

angle adjustment screw ②



angle adjustment screw ①


Record Head Height and Zenith Adjustment

Setting:

MONITOR switch: TAPE

Procedure:


Mode: record and simultaneous playback
PLAYBACK HEAD switch: 2 TRACK




Turn the height and zenith adjustment screws for the highest VTVM reading.

Adjustment Location:

— head base —




1. Mode: record and simultaneous playback



Turn the adjustment screws for the highest VTVM reading. If the highest peaks for L and R do not coincide, place the adjustment screws to the point where both L and R outputs are same and within 1 dB from the peaks.

2. Mode: record and simultaneous playback




Adjust	On the oscilloscope			
azimuth adjustment screw				
	good		wrong	

Note: Difference between the highest levels of L and R and the finally adjusted level should be within 1 dB.

Adjustment Location:

— head base —



Record Head Azimuth and Phase Adjustments

Setting:

MONITOR switch: TAPE

Procedure:

When a simplified test is made, follow Procedure 1. When an oscilloscope is available, employ Procedure 2.

Note: The two adjustment screws are so constructed to react each other. When one side screw is loosened, tighten another screw in the same angle.


Record Bias Adjustment

Setting:


MONITOR switch: TAPE

Procedure:

Mode: record and simultaneous playback




As trimmer capacitor C135 (L-CH) or C335 (R-CH) is slowly turned clockwise, VTVM reading will go up to a maximum and then start falling again. Adjust the capacitor until VTVM reads 0.5 dB below and beyond the maximum reading.



Adjustment Location:

— audio amp board —




Record Level Adjustment

Setting:

MONITOR switch: TAPE

Procedure:


Mode: record and simultaneous playback



Adjust	VTVM reading
RV103 (L-CH) RV303 (R-CH)	0.44 V (-5 dB)

Adjustment Location:

— audio amp board —




Record Equalizer Adjustment

Setting:

MONITOR switch: TAPE

Procedure:

Mode: record and simultaneous playback




	Adjust	Remarks
1 kHz	L102 (L-CH) and L302 (R-CH)	Same LINE OUT level at both frequencies.
25 kHz		

Level-difference allowance of 25 kHz signal from 1 kHz: 0 dB - -3 dB

Adjustment Location:

- audio amp board -




Record Bias Trap Adjustment

Setting:

MIC REC control: 0
LINE REC control: 0

Procedure:


Mode: record



Adjust	VTVM reading
L106 (L-CH) L306 (R-CH)	minimum

Adjustment Location:

- audio amp board -




Dummy Coil Adjustment

Setting:

MONITOR switch: TAPE

Procedure:


Mode: record and simultaneous playback



Step	Mode	Adjust	Remarks
1	stereo record and simultaneous playback	-	Record VTVM reading.
2	L channel record and simultaneous playback	L307	same VTVM reading as in step 1.
3	R channel record and simultaneous playback	L107	

Adjustment Location:

- audio amp board -





SECTION 4
DIAGRAMS

4-1. MOUNTING DIAGRAM — Amplifier Section (US, Canadian model) —




— Conductor Side —

Replacement Semiconductors
For replacement, use semiconductors except in ().



Q101, 103, 104
Q115, 121, 122
Q301, 303, 304
Q315, 321, 322
Q102, 108
Q302, 308



Q105, 109
Q123, 124
Q305, 309
Q323, 324





Q106
Q110-114, 120
Q306
Q310-314, 320
Q502, 503
Q506-508



Q125, 325: 2SC1475 (2SC1318)
Q505: 2SC1475-13 (2SC1475)



(After replacing Q505, perform the record bias adjustment on page 22.)

D101, 102
D301, 302
D502-504
D103
D303




D101, 102
D301, 302
D502-504
D103
D303


Q116, 316: 2SK43-13 (2SK43)



Q117, 317: 2SA705




D501: EQB01-11Z (EQA01-11S)




Note:

- : part mounted on the conductor side.
- B+ pattern.
- : signal path (both channel)
- : L-CH
- : R-CH
- DC resistance measurements are with coils connected on the circuit board, and are approximate.
- Color code of sleeving over the end of the jacket.




- Readings are taken under no signal conditions and in stop mode with a VOM (20 kΩ/V).
- (): record mode.
- (): forward mode.
- (): S607 is ON.
- AC voltage readings indicated by * in the bias oscillator circuit are taken with a VTVM.








Q	115	117	508	504	317	315	101	102	104	105	106
	122	121	503	501	323	321	301	302	303	304	306
D	102	501	504	302							

TC-765 TC-765



L BOARD


33 301
33 301




Q	115	117	508	504	317	315	101	102	104	105	106	109	114	113	505	314	313	124	507	
	120	116	503	501	323	321	301	302	103	303	506	108	110	312	311	110	310	125	325	
D		102	501	504		302						301	101				502	103	303	
																			503	324

TC-765 TC-765

4-2. SCHEMATIC DIAGRAM – Amplifier Section (US, Canadian model) –





- Note:**
- Components for right channel have the same values as for left channel. Reference numbers are coded from 301 (REC AMP or PB AMP) or 401 (PB AMP).
 - All capacitors are in μF unless otherwise noted. $\text{pF} = \mu\mu\text{F}$. 50WV or less are not indicated except for electrolytics.
 - All resistors are in ohms, $\frac{1}{4}\text{W}$ unless otherwise noted. $\text{k}\Omega = 1000\Omega$, $\text{M}\Omega = 1000\text{k}\Omega$.
 - All variable and adjustable resistors have characteristic curve B, unless otherwise noted.
 - : fusible resistor.
 - : low-noise capacitor and resistor.
 - : B+ bus.
 - : panel designation.
 - : adjustment for repair.
 - : chassis ground.
 - Voltages are dc with respect to ground unless otherwise noted.
 - Readings are taken under no signal conditions and in stop mode with a VOM (20 $\text{k}\Omega/\text{V}$).
 - (()) : record mode.
 - () : forward mode.
 - < > : S607 is ON.
 - AC voltage readings indicated by * in the bias oscillator circuit are taken with a VTVM.
 - Voltage variations may be noted due to normal production tolerances.
 - Switch

Ref. No.	Switch	Position
S101,301	MIC ATT	0 (dB)
S102,302	EQ	NORMAL
S103,303	REC MODE	PB
S104,304	MONITOR	TAPE
S501	BIAS	MED

4-3. MOUNTING DIAGRAM — Amplifier Section (UK, AEP, PX model) —


— Conductor Side —

Replacement Semiconductors
For replacement, use semiconductor except in ().

- Q101, 103, 104
- Q115, 121, 122
- Q126
- Q301, 303, 304
- Q315, 321, 322
- Q326
- Q102, 108
- Q302, 308

2SC1345-E (2SC458D)



Q501: 2SK30A



- Q105, 109
- Q123, 124
- Q305, 309
- Q323, 324

2SC634A (2SC458D)

Q504: 2SC1173





- Q106
- Q110-114, 120
- Q306
- Q310-314, 320
- Q502, 503
- Q506-509

2SC634A (2SC1363)


Q125, 325: 2SC1475 (2SC1318)

Q505: 2SC1475-13 (2SC1475)



(After replacing Q505, perform the record bias adjustment on page 22.)

- Q116, 316: 2SK43-13 (2SK43)




D101, 102

D301, 302


D103

D303


1T22A (1T22)



- Q117, 317: 2SA705
- Q127, 327: 2SA678 (2SA677)




D501: EQB01-11Z (EQA01-11S)




Note:

- : part mounted on the conductor side.
- : B+ pattern.
- : signal path (both channel)
- : L-CH
- : R-CH
- DC resistance measurements are with coils connected on the circuit board, and are approximate.
- Color code of sleeving over the end of the jacket.









- Readings are taken under no signal conditions and in stop mode with a VOM (20 kΩ/V).
- () : record mode.
- () : forward mode.
- < > : S607 is ON.
- AC voltage readings indicated by * in the bias oscillator circuit are taken with a VTVM.



Q	509	326	327	115	117	508	504	317	315	101	102	104	105	106	506
		126	127	120	116	503	502	323	321	301	302	303	304	305	306
D	505			102		504		302							301


TC-765 TC-765




27	115	117	508	504	317	315	101	102	104	105	106	109	114	113	505	112	111	314	313	124	507	
27	120	121	503	502	323	322	301	302	303	305	307	308	309	312	311	310				125	325	324
	102		501	504	302							301	101			502				103	303	503

TC-765 TC-765

4-4. SCHEMATIC DIAGRAM — Amplifier Section (UK, AEP, PX model) —






- Note:**
- Components for right channel have the same values as for left channel. Reference numbers are coded from 301 (REC AMP or PB AMP) or 401 (PB AMP).
 - All capacitors are in μF unless otherwise noted. $\text{pF} = \mu\text{F} \cdot 50\text{WV}$ or less are not indicated except for electrolytics.
 - All resistors are in ohms, $\frac{1}{2}\text{W}$ unless otherwise noted. $\text{k}\Omega = 1000\Omega$, $\text{M}\Omega = 1000\text{k}\Omega$
 - All variable and adjustable resistors have characteristic curve B, unless otherwise noted.
 - (N) : low-noise capacitor and resistor.
 - \square : B+ bus.
 - \square : panel designation.
 - \square : adjustment for repair.
 - --- : chassis ground.
 - Voltages are dc with respect to ground unless otherwise noted.
 - Readings are taken under no signal conditions and in stop mode with a VOM (20 $\text{k}\Omega/\text{V}$).
 - (()) : record mode.
 - () : forward mode.
 - < > : S607 is ON.
 - AC voltage readings indicated by * in the bias oscillator circuit are taken with a VTVM.
 - Voltage variations may be noted due to normal production tolerances.
 - Switch




Ref. No.	Switch	Position
S101,301	MIC ATT	0 (dB)
S102,302	EQ	NORMAL
S103,303	REC MODE	PB
S104,304	MONITOR	TAPE
S106,306	INPUT SELECT	LINE
S501	BIAS	MED

4-5. MOUNTING DIAGRAM - System Control Section -





- Conductor Side -



Q, IC	903	902	IC902	901	741	745	742	743	744	719	718	IC701	713	714	710	711	726	730	706	728	732	731	703	707	708	705	702																
D	739	755	909	906	902, 903	747	748	749	763	762	769	760	759	761	723	748	725	734	715	716	717	718	719	720	721	722	723	724	725	726	727	728	729	730	731	732	733	701	702	744	745	746	747



TC-765 TC-765





Note:

- ⊞ : B+ pattern.
- Color code of sleeving over the end of the jacket.

Readings are taken in stop mode with a VOM (20 kΩ/V).

(()): record mode.
()): forward mode.
(<)): S607 is ON.





Note:


- All capacitors are in μF unless otherwise noted. $\text{pF} = \mu\mu\text{F}$
- 50V or less are not indicated except for electrolytics.
- All resistors are in ohms, $\frac{1}{4}\text{W}$ unless otherwise noted. $\text{k}\Omega = 1000\Omega$, $\text{M}\Omega = 1000\text{k}\Omega$
- : fusible resistor.
- (N) : low-noise capacitor and resistor.
- 20% indicates component tolerance.
- : B+ bus.
- : panel designation.
- : adjustment for repair.
- : direct connection to points marked on the chassis.
- : chassis ground.
- Voltages are dc with respect to ground unless otherwise noted.
- Readings are taken in stop mode with a VOM (20 $\text{k}\Omega/\text{V}$).
- () : record mode.
- () : forward mode.
- : S607 is ON.
- Voltage variations may be noted due to normal production tolerances.
- Switch

Ref. No.	Switch	Position
S601	REEL SIZE	10 $\frac{1}{2}$
S602	TAPE SPEED	19 cm
S603	TIMER	OFF
S604	POWER	OFF
S605	SHUT-OFF (SUPPLY)	OFF
S606	SHUT-OFF (TAKE-UP)	OFF
S607	REC MONITOR MUTE	OFF


Replacement Semiconductor
For replacement, use semiconductors except in ().

- Q701, 703, 704
Q706, 707, 709
Q716-720, 722-735 : 2SC634A (2SC1364)
Q737, 738, 740-748
Q902


IC701: CX738




Q702, 705, 708: 2SC1061




IC901: CX065A (CX065)




Q710, 712, 714: 2SC1364 (BLUE) (2SC1364)




- D601, 708-713
D715, 718-720 : 1S1555 (1T40)
D723-743
D748-754
D759-767
D714:
D769: 1T22A (1T22)
1S1555



Q711, 713, 715: 2SC1475-13 (2SC1475)




- D602, 603
D701-705
D707, 716, 717 : 10E2 (SIB01-02)
D744-747
D755-758
D901, 906-909




After replacing Q711, 713 or Q715, change the resistor as follows.

- Q711: R722 10 $\text{k}\Omega \rightarrow 8.2 \text{k}\Omega$
Q713: R725 10 $\text{k}\Omega \rightarrow 8.2 \text{k}\Omega$
Q715: R728 10 $\text{k}\Omega \rightarrow 8.2 \text{k}\Omega$


Q736, 739: 2SC867A (2SC867)
Q903: 2SC867A





D706, 768: EQB01-11Z (EQA01-11R)




Q901: 2SA678 (2SA677)



D904, 905: VD1221 x 2




Note: The components identified by shading are critical for safety. Replace only with part number specified.



Note:

- Items with no part number and/or no description are not stocked because they are seldom required for routine service.
- All screws are Phillips (cross recess) type unless otherwise noted.
- (-) = slotted head
- Circled letters (A to Z) are applicable to European models only.
- (□□T) shows the number of coils in spring.



Note:

- Items with no part number and/or no description are not stocked because they are seldom required for routine service.
- All screws are Phillips (cross recess) type unless otherwise noted.
- (-) = slotted head
- Circled letters (A to Z) are applicable to European models only.

**SECTION 6
ELECTRICAL PARTS LIST**

Note: Circled letters (A to Z) are applicable to European models only.

<u>Ref. No.</u>	<u>Part No.</u>	<u>Description</u>
PRINTED CIRCUIT BOARD		
	1-585-576-00	(B) Meter
SEMICONDUCTORS		
Transistors		
⇒ Q101-104, ⇒ Q301-304	(B)	2SC1345-E
⇒ Q105,106 ⇒ Q305,306	(B)	2SC634A
⇒ Q108,308	(B)	2SC1345-E
⇒ Q109-114, ⇒ Q309-314	(B)	2SC634A
Q115,315	(B)	2SC1345-E
⇒ Q116,316	(E)	2SK43-13
Q117,317	(B)	2SA705
⇒ Q120,320	(B)	2SC634A
Q121,321 Q122,322	(B)	2SC1345-E
⇒ Q123,323 ⇒ Q124,324	(B)	2SC634A
⇒ Q125,325	(C)	2SC1475
Q126,326	(B)	2SC1345-E (AEP, UK, PX model)
⇒ Q127,327	(C)	2SA678 (AEP, UK, PX model)
Q501	(B)	2SK30A
⇒ Q502,503	(B)	2SC634A
Q504	(C)	2SC1173
⇒ Q505	(C)	2SC1475-13
⇒ Q506-508	(B)	2SC634A
⇒ Q509	(B)	2SC634A (AEP, UK, PX model)
⇒ Q701	(B)	2SC634A
Q702	(D)	2SC1061
⇒ Q703,704	(B)	2SC634A
Q705	(D)	2SC1061
⇒ Q706,707	(B)	2SC634A
Q708	(D)	2SC1061
⇒ Q709	(B)	2SC634A
⇒ Q710	(B)	2SC1364 (blue)

<u>Ref. No.</u>	<u>Part No.</u>	<u>Description</u>
⇒ Q711	(B)	2SC1475-13
⇒ Q712	(B)	2SC1364 (blue)
⇒ Q713	(C)	2SC1475-13
⇒ Q714	(B)	2SC1364 (blue)
⇒ Q715	(C)	2SC1475-13
⇒ Q716-720	(B)	2SC634A
⇒ Q722-735	(B)	2SC634A
Q736	(C)	2SC867A
⇒ Q737,738	(B)	2SC634A
Q739	(C)	2SC867A
⇒ Q740-748	(B)	2SC634A
⇒ Q901	(C)	2SA678
⇒ Q902	(B)	2SC634A
Q903	(C)	2SC867A
ICs		
IC701	(K)	CX738
⇒ IC901	(F)	CX065A
Diodes		
⇒ D101,301 ⇒ D102,302	(B)	1S1555
⇒ D103,303	(B)	1T22A
⇒ D501	(B)	EQB01-11Z
⇒ D502-504	(B)	1S1555
⇒ D505	(B)	1S1555 (AEP, UK, PX model)
⇒ D601	(B)	1S1555
D602,603	(B)	10E2
D701-705	(B)	10E2
⇒ D706	(B)	EQB01-11Z
D707	(B)	10E2
⇒ D708-713	(B)	1S1555
⇒ D714	(B)	1T22A
⇒ D715	(B)	1S1555
D716,717	(B)	10E2
⇒ D718-720	(B)	1S1555
⇒ D723-743	(B)	1S1555
D744-747	(B)	10E2

⇒: Due to standardization, interchangeable replacements may be substituted for parts specified in the diagrams.

Note: The components identified by shading are critical for safety. Replace only with part number specified.

TC-765 TC-765

Note: Circled letters (A to Z) are applicable to European models only.

Ref. No.	Part No.	Description
⇒ D748-754	Ⓑ 1S1555	
⇒ D755-755	Ⓑ 10E2	
⇒ D759-767	Ⓑ 1S1555	
⇒ D768	Ⓑ EQB01-11Z	
D769	Ⓑ 1S1555	
⇒ D901	Ⓑ 10E2	
D904,905	Ⓑ VD1221	
⇒ D906-909	Ⓑ 10E2	
Th701,702	1-800-204-00 Ⓑ	Thermistor S-10K

COILS

L101,301	1-407-593-00 Ⓑ	27 mH, microinductor
L102,302	1-407-269-00 Ⓑ	2.2 mH, variable inductor
L103,303	1-407-213-XX Ⓑ	1.5 mH, microinductor
L104,304	1-407-195-XX Ⓑ	1.2 mH, microinductor
L106,306	1-407-286-00 Ⓑ	2.2 mH, variable inductor
L107,307	1-407-248-00 Ⓑ	1 mH, variable inductor

TRANSFORMER

PT601	1-442-803-00	Power (US, Canadian model)
PT601	1-442-804-00	Power (UK, AEP, PX model)
T101,301	1-427-284-00 Ⓑ	Output

CAPACITORS

All capacitors are in μF and electrolytic unless otherwise noted.
50WV or less are not indicated except for electrolytics tantalum. $\text{pF} = \mu\text{F}$

C101,301	1-131-193-11 Ⓑ	10 10V tantalum
C102,302	1-107-131-11 Ⓐ	100p silvered mica
C103,303	1-121-410-11 Ⓑ	47 25V
C104,304	1-131-190-11 Ⓑ	22 6.3V tantalum
C105,305	1-131-236-11 Ⓑ	1 25V tantalum
C106,306	1-107-073-11 Ⓐ	33p silvered mica
C107,307	1-131-192-11 Ⓑ	4.7 10V tantalum
C108,308	1-121-416-11 Ⓑ	100 25V
C109,309	1-107-131-11 Ⓐ	100p silvered mica
C110,310	1-107-133-11 Ⓐ	120p silvered mica
C111,311	1-131-191-11 Ⓑ	47 6.3V tantalum
C112,312	1-131-207-11 Ⓑ	4.7 25V tantalum

Ref. No.	Part No.	Description
C113,313	1-121-391-11 Ⓐ	1 50V
C114,314	1-108-816-12 Ⓑ	0.1 mylar
C116,316	1-131-193-11 Ⓑ	10 10V tantalum
C117,317	1-121-654-11 Ⓑ	330 25V
C118,318	1-131-190-11 Ⓑ	22 6.3V tantalum
C119,319	1-121-805-11 Ⓑ	330 10V
C120,320	1-131-238-11 Ⓑ	10 25V tantalum
C121,321	1-108-795-12 Ⓐ	0.0018 mylar
C122,322	1-108-808-12 Ⓐ	0.022 mylar
C123,323	1-108-808-12 Ⓐ	0.022 mylar
C134-126	1-108-805-12 Ⓐ	0.012 mylar
C324-326		
C127,327	1-108-804-12 Ⓐ	0.01 mylar
C128,328	1-108-806-12 Ⓐ	0.015 mylar
C129,329	1-107-185-11 Ⓐ	470p silvered mica
C130,330	1-107-037-11 Ⓐ	82p silvered mica
C131,331	1-107-163-11 Ⓐ	47p silvered mica
C132-134	1-101-001-11	0.001 ceramic (US, Canadian model)
C332-334		
C135,335	1-141-010-XX Ⓑ	Trimmer
C201,401	1-131-195-11 Ⓑ	33 10V tantalum
C202,402	1-107-131-11 Ⓐ	100p silvered mica
C203,403	1-121-410-11 Ⓑ	47 25V
C204,404	1-107-123-11 Ⓐ	47p silvered mica
C205,405	1-131-187-11 Ⓑ	100 3.15V tantalum
C206,406	1-104-052-11 Ⓑ	0.015 125V polystyrol
C207,407	1-131-238-11 Ⓑ	10 25V tantalum
C208,408	1-103-765-11 Ⓐ	390p polystyrol
C209,409	1-121-391-11 Ⓐ	1 50V
C210,410	1-107-135-11 Ⓐ	150p silvered mica
C211,411		
C212,412	1-131-190-11 Ⓐ	22 6.3V tantalum
C213,413	1-121-416-11 Ⓑ	100 25V
C214,414	1-107-102-11 Ⓐ	5p silvered mica
C215,415	1-131-195-11 Ⓑ	33 10V tantalum
C216,416	1-108-814-12 Ⓑ	0.068 mylar
C217,417	1-131-208-11 Ⓒ	6.8 25V tantalum
C218,418	1-107-123-11 Ⓐ	47p silvered mica
C219,419	1-131-192-11 Ⓑ	4.7 10V tantalum
C220,420	1-121-398-11 Ⓐ	10 25V
C221,421	1-121-352-11 Ⓐ	47 10V

Note: Circled letters (A to Z) are applicable to European models only.

Ref. No.	Part No.	Description
C251,451	1-131-197-11 Ⓑ	3.3 16V tantalum (AEP, UK, PX model)
C252,452	1-107-139-11 Ⓐ	220p silvered mica (AEP, UK, PX model)
C253,453	1-131-207-11 Ⓑ	4.7 25V tantalum (AEP, UK, PX model)
C254,454	1-121-416-11 Ⓑ	100 25V
C501	1-121-738-11 Ⓐ	10 50V
C502	1-121-415-11 Ⓑ	100 16V
C503	1-121-480-11 Ⓐ	22 25V
C504	1-121-398-11 Ⓐ	10 25V
C505	1-121-450-11 Ⓐ	2.2 50V
C506	1-129-703-11 Ⓑ	0.0012 630V polyethylene
C507	1-108-804-12 Ⓐ	0.01 mylar
C508-510	1-121-398-11 Ⓐ	10 25V
C511	1-101-001-11 Ⓐ	0.001 ceramic
C512,513	1-101-001-11 Ⓐ	0.001, ceramic (AEP, UK, PX model)
C601	1-108-750-22	Ⓑ 0.033 500V, metalized paper (AEP, UK, PX model)
C701-703	1-121-061-11	Ⓒ 1000 50V
C704	1-121-411-11 Ⓑ	47 50V
C705	1-121-409-11 Ⓐ	47 16V
C706	1-121-398-11 Ⓐ	10 25V
C707	1-121-391-11 Ⓐ	1 50V
C708	1-121-657-11	Ⓑ 1000 25V
C709	1-121-415-11 Ⓑ	100 16V
C710	1-121-395-11 Ⓐ	4.7 25V
C711	1-121-450-11 Ⓐ	2.2 50V
C712	1-121-395-11 Ⓐ	4.7 25V
C713	1-121-396-11 Ⓐ	4.7 50V
C714	1-108-246-12	Ⓐ 0.047
C715	1-108-246-12 Ⓐ	0.047
C716	1-121-480-11 Ⓐ	22 25V
C717	1-121-409-11 Ⓐ	47 16V
C718	1-121-480-11 Ⓐ	22 25V
C719	1-121-395-11 Ⓐ	4.7 25V
C720	1-121-415-11 Ⓑ	100 16V
C721	1-108-246-12 Ⓐ	0.047 mylar
C722-726	1-108-239-12 Ⓐ	0.01 mylar
C727	1-108-234-12 Ⓐ	0.047 mylar
C728	1-108-239-12 Ⓐ	0.01 mylar

Ref. No.	Part No.	Description
C729,730	1-102-110-11 Ⓐ	220p ceramic
C731,732	1-108-244-12 Ⓐ	0.033 mylar
C733	1-121-132-11	Ⓐ 4.7 50V
C734	1-131-205-11 Ⓑ	2.2 25V tantalum
C735	1-121-450-11 Ⓐ	2.2 50V
C736	1-121-398-11 Ⓐ	10 25V
C737	1-121-396-11 Ⓐ	4.7 50V
C738	1-108-967-11	Ⓒ 0.47 200V polyethylene
C739	1-117-100-11	Ⓐ 10 150V metalized paper
C740,741	1-121-395-11 Ⓐ	4.7 25V
C742	1-108-967-11	Ⓒ 0.47 200V polyethylene
C743	1-117-100-11	Ⓐ 10 150V metalized paper
C744	1-121-398-11 Ⓐ	10 25V
C745	1-121-450-11 Ⓐ	2.2 50V
C746	1-121-395-11 Ⓐ	4.7 25V
C747	1-108-239-12 Ⓐ	0.01 mylar
C748	1-102-074-11 Ⓐ	0.001 ceramic
C749	1-121-395-11 Ⓐ	4.7 25V
C750	1-121-398-11 Ⓐ	10 25V
C751	1-121-409-11 Ⓐ	47 16V
C752	1-121-398-11 Ⓐ	10 25V
C753	1-121-986-11 Ⓐ	2.2 50V
C901	1-121-416-11 Ⓑ	100 25V
C902	1-121-398-11 Ⓐ	10 25V
C903	1-129-793-11 Ⓑ	0.047 100V polyethylene
C904	1-108-593-12 Ⓑ	0.039 mylar
C905	1-108-240-12 Ⓐ	0.015 mylar
C906	1-121-450-11 Ⓐ	2.2 50V
C907	1-121-398-11 Ⓐ	10 25V
C908	1-121-961-11 Ⓐ	4.7 25V
C909,910	1-131-211-11 Ⓑ	0.22 35V tantalum
C911	1-121-968-11 Ⓐ	10 16V
C912	1-121-951-11 Ⓐ	0.47 50V
C913	1-121-980-11 Ⓐ	100 6.3V
C914	1-121-961-11 Ⓐ	4.7 25V
C915	1-121-759-11 Ⓑ	4.7 250V

⇒: Due to standardization, interchangeable replacements may be substituted for parts specified in the diagrams.

Note: The components identified by shading are critical for safety. Replace only with part number specified.

Note: The components identified by shading are critical for safety. Replace only with part number specified.


Note: Circled letters (A to Z) are applicable to European models only.

ACCESSORIES & PACKING MATERIALS	
<u>Part No.</u>	<u>Description</u>
A-2500-027-A	RM-30 (US, Canadian, PX model)
X-3552-801-0	Carton Ass'y (US model)
X-3552-802-0	(K) Carton Ass'y (Canadian, AEP, UK model)
X-3552-803-0	Carton Ass'y (PX model)
1-526-565-00	Adaptor, AC plug (PX model)
1-534-049-31	(F) Cord, connection; RK-74H
1-534-754-00	Cord, power (PX model)
1-534-819-00	(G) Cord, power 3 pin (UK model)
3-401-193-00	Ribbon, head cleaning (US model)
3-534-322-00	(A) Cushion, reel table
3-534-327-00	(C) Case, reel
3-541-496-00	(D) Bag, protection
3-542-008-00	(C) Tips, head cleaning
3-542-101-00	(B) Adaptor, reel
3-551-428-00	(B) Cover, sheet
3-551-428-00	(B) Cushion, lower
3-551-430-00	(D) Cushion upper
3-552-909-00	Carton, RM-30 (PX, US, Canadian model)
3-701-628-00	Bag, plastic; RM-30 (US, Canadian, PX model)
3-701-632-11	(I) Manual, instruction (AEP, UK model)
3-770-226-21	Manual, instruction (US model)
3-770-226-31	Manual, instruction (Canadian model)
3-770-226-61	Manual, instruction (PX model)


Note: The components identified by shading are critical for safety. Replace only with part number specified.

HARDWARE NOMENCLATURE

Screw:



Nut, Washer, Retaining ring:



Reference Designation	Shape	Description	Remarks
SCREWS			
P		pan-head screw	binding-head (B) screw for replacement
PWH		pan-head screw with washer face	binding-head (B) screw and flat washer for replacement
PS PSP		pan-head screw with spring washer	binding-head (B) screw and spring washer for replacement
PSW PSPW		pan-head screw with spring and flat washers	binding-head (B) screw and spring and flat washers for replacement
R		round-head screw	binding-head (B) screw for replacement
K		flat-countersunk-head screw	
RK		oval-countersunk-head screw	
B		binding-head screw	
T		truss-head screw	binding-head (B) screw for replacement
F		flat-fillister-head screw	
RF		fillister-head screw	
BV		braizer-head screw	

Reference Designation	Shape	Description	Remarks
SELF-TAPPING SCREWS			
TA		self-tapping screw	ex: TA, P 3 x 10
PTP		pan-head self-tapping screw	binding-head self-tapping (TA, B) screw for replacement
PTPWH		pan-head self-tapping screw with washer face	binding-head self-tapping (TA, B) screw and flat washer for replacement
PTTWH		pan-head thread-rolling screw with washer face	binding-head (B) screw and flat washer for replacement
SET SCREWS			
SC		set screw	
SC		hexagon-socket set screw	ex: SC 2.6 x 4, hexagon socket
NUT			
N		nut	
WASHERS			
W		flat washer	
SW		spring washer	
LW		internal-tooth lock washer	ex: LW3, internal
LW		external-tooth lock washer	ex: LW3, external
RETAINING RINGS			
E		retaining ring	
G		grip-type retaining ring	