



RESISTANCE READINGS

ITEM	TUBE	Pin 1	Pin 2	Pin 3	Pin 4	Pin 5	Pin 6	Pin 7	Pin 8	Pin 9
V1	ECC83 12AX7	↑490K	70K	1800Ω	205Ω	205Ω	↑490K	70K	1800Ω	205Ω
V2	ECC82 12AU7	↑140K	3.3meg	0Ω	205Ω	205Ω	↑140K	3.3meg	0Ω	205Ω
V3	ECC82 12AU7	↑60K	0Ω	1200Ω	205Ω	205Ω	60K	0Ω	1200Ω	205Ω
V4	ECC83 12AX7	↑190K	↑10meg	150K	205Ω	205Ω	↑150K	0Ω	680Ω	205Ω
V5	EL84 6BQ5	TP	470K	180Ω	205Ω	205Ω	NC	↑170Ω	TP	↑1000Ω
V6	EL84 6BQ5	TP	470K	180Ω	205Ω	205Ω	NC	↑215Ω	TP	↑1000Ω
V7	ECC83 12AX7	↑190K	↑10meg	150K	205Ω	205Ω	↑150K	0Ω	680Ω	205Ω
V8	EL84 6BQ5	TP	470K	180Ω	205Ω	205Ω	NC	↑170Ω	TP	↑1000Ω
V9	EL84 6BQ5	TP	470K	180Ω	205Ω	205Ω	NC	↑215Ω	NC	↑1000Ω
V10	6Z54 5AR4	TP	1	NC	40Ω	TP	40Ω	TP	1	

↑ THIS READING WILL VARY DEPENDING UPON THE CONDITION OF THE ELECTROLYTIC IN THE CIRCUIT.
 1 MEASURED FROM PIN 8 OF V10.
 2 MEASURED FROM PIN 3 OF V4.
 3 MEASURED FROM PIN 3 OF V7.
 NC NO CONNECTION
 TP TIE POINT

FUNCTION SWITCH M3 SHOWN IN No 1 POSITION
 1. PHONO LOW - TAPE LOW
 2. PHONO HI
 3. TUNER
 4. AUX-TAPE HI

MODE SWITCH M2 SHOWN IN No 1 POSITION
 1. REVERSE
 2. STEREO
 3. MONOPHONIC
 4. RIGHT
 5. LEFT

● SEE PARTS LIST FOR ALTERNATE VALUE OR APPLICATION
 DC COIL RESISTANCE VALUES UNDER ONE OHM NOT SHOWN ON SCHEMATIC DIAGRAM

1. DC voltage measurements taken with vacuum tube voltmeter;
 AC voltages measured at 1000 ohms per volt.
 2. Socket connections are shown as bottom views.

