

marantz®

MA-9S1 Power Amplifier

SC-7S1/MA-9S1. The audio community has never forgotten the Marantz Model 9 monophonic power amplifier. Now, more than 40 years later, this product still stands as an ideal fusion of original circuit design and outstanding aesthetic appeal. Indeed, one of the main forces that established the Marantz reputation - and remain a source of inspiration for many designers and enthusiasts.



Today, the distinctive voices of the original Model 9 is reborn in the MA-9S1 monaural power amplifier. This work of art defines new horizons in both musical performance and contemporary elegance. The MA-9S1 is an enduring testament to the synergy of today's advances in physics, electronic circuitry, and metallurgy guided by our unwavering respect for the past.

That is why we assigned to these products model numbers directly traceable of our heritage. When you hear them, you'll understand.



FEATURES

| | |
|--|-------------|
| Number of Channels | 1 |
| Output Power/Channel (20Hz - 20kHz) @ 8Ω | 300W |
| HDAM | • (HDAM SA) |
| Power Transformer | Toroidal |
| Discrete Amplifier Stage | • |
| Individual Level Adjust | • |

IN/OUTPUTS

AUDIO

| | |
|---------------------|-------------------------------------|
| Analog L&R In | - |
| Main Channel Amp In | 1/1 (Balanced Mono/Unbalanced Mono) |
| Bridge Mono Mode | - |
| Analog L&R Out | - |
| Headphone Out | - |

OTHERS

| | |
|----------------------------|---|
| D-Bus Remote (RC-5) In/Out | - |
| External Control | - |

SPECIFICATIONS

| | |
|-----------------------------|-------------------------|
| THD (20Hz - 20kHz, 8Ω) | 0.01% |
| Input Sensitivity/Impedance | 1.7V/20kΩ |
| Frequency Response | 3Hz - 120kHz (+0, -3dB) |
| S/N Ratio | 120dB |

GENERAL

| | |
|-------------------------------|---|
| Color | Gold |
| Front Panel | Aluminum |
| Remote Control | - |
| Power Requirement | AC 120V 60Hz |
| Power Consumption | 500W |
| Dimensions (Inches) W x H x D | 18" x 7 ^{1/16} " x 17 ^{1/4} " |
| Weight (lbs.) | 78.9 |

*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors within this document.