

AM/FM/XM STEREO TUNER



The ST7001 continues the legendary Marantz tradition of tuner performance with a digitally-synthesized “front end” optimized for both high sensitivity and high selectivity. This makes the ST7001 a great choice for both urban and rural areas. The audio circuitry follows this same high-quality pattern with custom-selected parts in a meticulous layout to maximize signal quality while minimizing interference. In addition, the ST7001 boasts a wide variety of convenience features including 100-station programmability with custom naming to help you get to your favorite broadcasts easily. The sleep timer function lets you fall asleep to the station of your choice. The D-Bus connector and supplied remote control make this tuner a cinch to integrate with the most advanced custom designed systems.

- XM-Ready (Connect and Play)
- AM/FM Stereo Tuner
- Triple IR Code Sets
- Total 100 Station Pre-set Memory (10 groups x 10 Stations) for AM/FM
- Editable Station Name
- Discrete All XM channel codes
- Dual Analog Audio Outputs
- RS232C Connection for System Control
- Direct IR Flasher Input
- Detachable Power Code
- Aluminum Front panel
- Weekly Timer
- Sleep Timer
- Timer-controlled AC Outlet



FEATURES

HDAM	-
XM-Ready	•
Chassis	Metal
Customized Components	-
Preset Station Memory	100
Station Naming	•
Sleep Timer	•

IN/OUTPUTS

AUDIO

Analog L&R OUT	2
D-Bus remote (RC-5) In/Out	•
FM Antenna	•
AM Antenna	•

GENERAL

Color	Black
Front Panel	Aluminum
Remote Control	Device Remote RC7001ST
Power Requirements	AC 120V 60Hz
Power Consumption	12W
Dimensions W x H x D (Inches)	17 ⁵ / ₁₆ " x 3 ¹ / ₁₆ " x 14 ³ / ₁₆ "
Weight (lbs.)	9.0

SPECIFICATIONS

TUNER SECTION FM

Frequency Range	87.5 - 108.0MHz
S/N Ratio (Mono/Stereo)	74/68 dB
Distortion (Mono/Stereo)	0.2/0.3 %
Selectivity (Wide/Narrow)	50 dB
Usable Sensitivity	1.1 V
Stereo Separation	43 dB

TUNER SECTION AM

Frequency Range	520 - 1710kHz
S/N Ratio	53 dB
Distortion	-
Sensitivity	18 V

marantz[®]
LIFE AMPLIFIED™