

Marantz CC-3000 and CC-4000 Carousel CD Changers: Outstanding Performance and Value.



CC-3000 and CC-4000

Audio System

Frequency range	20 Hz - 20 kHz
Amplitude non-linearity	≤ 3 dB (1 kHz, -90 dB)
Dynamic range	>90 dB (1 kHz)
Singal to noise ratio	>95 dB (1 kHz)
Channel separation	>95 dB (1 kHz)
Channel balance	≤ 1 dB (1 kHz)
Total harmonic distortion	0.004% (1 kHz)
Audio output level	2 Vrms, ± 2 dB, 1 kΩ
Impedance Phones socket (6.5mm)	30 - 600 Ω
Digital coaxial output	(4.5 V e.m.f. from 120 Ω) 75Ω acc IEC 958

General

Power requirements	120 V, 60 Hz, 12 W
Dimensions W/H/D	17 ³ / ₈ " x 4 ³ / ₄ " x 15"
Weight	440mm x 119mm x 380mm 13.3 lbs. 6.0 kg.

The Marantz CC-3000 and CC-4000 5-disc CD changers combine outstanding CD playback quality and exceptional value. Both models incorporate identical components and features found in high-end Marantz models, for richly detailed, musically involving CD sound quality. The CC-3000 includes all the features of the CC-4000 with the exception of a headphone jack with level control.

CC-3000 and CC-4000 Features:

Precision optics, mechanism and digital circuitry including the Philips full-floating laser mechanism and digital servo control. A Bitcheck Continuous Calibration D/A converter (CC-4000 only) is used for ultra-precise disc tracking and exceptionally accurate reconstruction of the musical signal.

Quick Logic bi-directional carousel mechanism accesses discs in the shortest possible time, and allows up to three discs at a time to be exchanged while another disc is playing.

D-BUS remote connection allows linkage to other Marantz components for integrated system operation. Full remote control operation is also provided.

CD-RW playback capability-until now, CD-RW rewritable discs could only be played back on specialized CD-RW-capable recording decks.

Full complement of programming and play modes and convenience features including a variety of random play, repeat and shuffle options, peak level search, music scan, 40-track programming, headphone jack with level control (CC-4000 only) and more.

Edit mode automatically fits the tracks on a CD to accommodate the length of a cassette or recordable CD.

Coaxial digital output enables use with outboard D/A converters, or connection to the digital input of an A/V receiver or preamp/processor.

Fade-in and Fade-Out Capability.



marantz®

Marantz America, Inc. 440 Medinah Road Roselle, IL 60172
Phone 630-307-3100 • Fax 630-307-2687 • www.marantz.com