



ALIGNMENT INSTRUCTIONS

Use only enough generator output to provide a usable indication.
 Suggested Alignment Tools: GENERAL CEMENT #5097, 8727... WALSCO #2515

MULTIPLEX ADAPTER ALIGNMENT USING FM STEREO GENERATOR & AUDIO OSCILLATOR

| | SIGNAL GENERATOR | CONNECT SCOPE | ADJUST | REMARKS |
|----|---|---|--------|---|
| 1. | 19KC to MPX input, low side to chassis. | Vert. Amp. to pin 2 of V2, low side to chassis. | A1 | Adjust for maximum deflection. Set scope to lock in 2 cycles. |
| 2. | " | Vert. Amp. to point A low side to chassis. | A2 | Adjust for maximum deflection of 4-cycle waveform. |
| 3. | 67KC to MPX input, low side to chassis. | " | A3, A4 | Adjust for MINIMUM deflection. |



HARMAN-KARDON MX600