





HITACHI

**Hitachi Model WH888L:** Eight-transistor, two-wave-band portable receiver with "Radar" pilot light tuning indicator controlled from A.G.C. with D.C. amplifier. Two earphone jacks. Six-volt battery (four 1.5-volt cells), batteries can be replaced without removing cabinet back. For cord-drive diagram see page 142.

**Wavebands:** M.W. 530-1605 kc/s.; L.W. 155-350 kc/s.

**Semiconductors:** See circuit diagram for types and functions.

**Alignment:** I.F. 455 kc/s. (T<sub>3</sub>, T<sub>2</sub>, T<sub>1</sub>); L.W. 145 kc/s. (L<sub>4</sub>); 360 kc/s. (C<sub>12</sub>); 160 kc/s. (L<sub>2</sub>); 330 kc/s. (C<sub>3</sub>); M.W. 515 kc/s. (L<sub>3</sub>); 1650 kc/s. (C<sub>9</sub>); 600 kc/s. (L<sub>1</sub>); 1400 kc/s. (C<sub>2</sub>).