



Commutatore su onde lunghe
 Gli zoccoli delle valvole sono
 usati dal di sotto

Planchetta vista
 dall'interno

SCHEMA ELETTRICO DEL TELEFUNKEN 779-783

TELEFUNKEN

VALVOLE: 1) WE 43 1) WE 33 1) WE 37
VALORI CONDENSATORI

15	50 pF	52	5-30 pF
18	5-30 pF	53	14-16 pF
22	25 pF	54	1000 pF
23	5-30 pF	55	30000 ohm
25	25-60 pF	56	20000 pF
26	5-30 pF	57	2500 ohm
27	25-60 pF	58	20000 pF
28	5-30 pF	59	200 pF
29	100000 pF	62	200 pF
30	1 M · ohm	63	20000 pF
31	25000 ohm	64	200 ohm
32	50 ohm	65	5000 pF
36	20000 pF	66	50000 ohm
37	50000 pF	67	20000 pF
38	200 ohm	68	50000 ohm
39	20000 ohm	70	20000 pF
40	100 pF	71	200 pF
51	25-60 pF	74	200 pF

TELEFUN

VALVOLE: 1) WE 43 2) WE 33
VALORI CONDENSATORI

9	5-30 pF	33	1000 pF
12	5-30 pF	34	30000 ohm
15	0,1 MF	35	20000 pF
19	25000 ohm	36	2500 ohm
20	50000 pF	37	20000 pF
21	5000 ohm	38	200 pF
20	5000 pF	41	200 pF
23	200 ohm	42	20000 pF
24	20000 ohm	43	200 ohm
25	100 pF	44	50000 pF
28	300 pF	45	5000 ohm
29	5-30 pF	46	20000 pF
32	5-30 pF	47	50 ohm

TELEFUNKEN

VALVOLE: 1) WE 43 2) WE 33
VALORI CONDENSATORI

14	5-30 pF	39	120 pF
17	25 pF	40	25-60 pF
18	5-30 pF	43	300 pF
20	50 pF	46	14-16
22	25-60 pF	47	5-30 pF
23	5-30	48	1000 pF
24	35-60	49	30000 ohm
25	5-30 pF	50	20000 pF
26	0,1 MF	51	2500 ohm
30	25000 ohm	52	20000 pF
31	20000 pF	53	200 pF
32	50000 ohm	56	200 pF
33	50000 pF	57	20000 pF
34	200 ohm	58	200 ohm
36	20000 ohm	59	50000 pF
36	100 pF	60	50000 ohm

779-783

1) WE 39 1) WE 38 1) WE 38 1) WE 53
E RESISTENZE

75	50 pF	92	8 MF
76	50 pF	93	8000 ohm
77	250 K · ohm	94	8 MF
78	100 K · ohm	95	8000 ohm
79	100 pF	96	1 M · ohm
80	1 M · ohm	97	20000 pF
81	2 M · ohm	98	20000 pF
82	2 M · ohm	99	300 pF
83	2 M · ohm	100	100000 ohm
84	20 pF	101	0,5 MF
85	0,2 M · ohm	102	50000 ohm
86	20000 pF	103	100000 pF
87	40000 ohm	105	10 MF
88	50 ohm	106	75 ohm
89	10 MF	107	5000 pF
90	4000 ohm	108	1300 pF
91	200 ohm	112-113	16 MF

KEN 559

3) WE 37 4) WE 38 5) WE 54
E RESISTENZE

48	1 M · ohm	63	100000 ohm
49	1 M · ohm	64	20000 pF
50	200 pF	65	500000 ohm
53	200 pF	66	0,25 MF
54	50 pF	67	100000 ohm
55	250000 ohm	68	1 M · ohm
56	100000 ohm	69	100 pF
57	50 pF	70	20000 pF
58	300 pF	71	0,5 M · ohm
59	2500 ohm	72-73	8 MF
60	10 MF	78	pF 2000
61	50000 ohm	78a	50 ohm
62	0,5 MF		

569-572

3) WE 37 4) WE 38 5) WE 54
E RESISTENZE

61	20000 pF	79	0,5 MF
62	50000 ohm	80	100000 ohm
64	2 M ohm	81	20000 pF
65	2 M ohm	82	500000 ohm
66	200 pF	83	0,25
69	200 pF	84	10000 ohm
70	50 pF	85	1 M · ohm
71	250 K · ohm	88	100 pF
72	100 K ohm	87	20000 pF
73	50 pF	88	0,5 M · ohm
74	20000 pF	89	10000 pF
75	300 pF	90	0,2 M · ohm
76	2500 ohm	91-92	8 MF
77	10 MF	97	1300 pF
78	50000 ohm	99	5000 pF