

## PROGRESSIVE SCAN UNIVERSAL DVD PLAYER



DV6600. Even though there are more “universal” disc players every day, quality players are difficult to find. The DV6600 combines universality and quality in a uniquely Marantz fashion. First, the DV6600 handles movie DVDs, DVD-As, SACDs, conventional music CDs, recordable CD-Rs and CD-RWs, VCD 2.0 discs, MP3 and WMA audio discs, and JPEG-format picture discs! Then, the way the DV6600 handles these discs truly sets it apart. The Marantz audio tradition extends well into the 21st Century with internal Dolby Digital and DTS decoders. Six of the finest 192kHz/24-Bit digital-to-analog converters make everything you play sound exceptionally lifelike. And you can even shut off the DV6600’s video circuitry completely for the purest audio signal path possible. Internal bass management circuits route DVD-A and SACD audio channels directly to the proper speakers. Video technology includes advanced 3:2 pull down circuitry and wide bandwidth video D/A converters for exceptional picture quality. Famed DCDi<sup>®</sup> deinterlacing and scaling will upconvert the video from any DVD to progressive scan and scale the output to 480p, 720p, or 1080i through the included HDMI output. Composite, S-Video, and component outputs? Progressive scan? Of course! We haven’t forgotten conveniences either. There’s an advanced on-screen display, parental controls, front panel menu operation, and a new hand-contoured remote. Connectivity options include audio and video outputs as well as a D-BUS connector for total system control. The three-year warranty shows our confidence and increases your peace of mind. Would you expect anything less from Marantz?

- Plays Back DVD-Video/Audio, SACD-Stereo/Multi-channel, DVD-R/RW, CD, CD-R/RW, SVCD, VCD, MP3, WMA JPEG and DivX Discs
- Built-in progressive scan (w/3:2 Pull down)/scaler for 480p, 1080i and 720p Output
- Faroudja DCDi<sup>™</sup> Processing
- 108MHz/12-Bit Video D/A Converter
- 192kHz/24-Bit Audio D/A Converters
- HDMI Output
- Audio EX Mode (Video Off)
- Dolby Digital<sup>®</sup>/DTS Decoder
- On Screen Display
- Parental Control
- Menu Operation From Front Panel
- Discrete Power On/Off
- Component, S-Video, Composite Outputs
- 5.1 ch Analog Audio Output
- Stereo Analog Audio Output
- Digital Audio Outputs (coaxial, optical)
- D-BUS (RC-5 In/Out) Remote Connection
- Device Remote

**marantz**<sup>®</sup>  
LIFE AMPLIFIED<sup>™</sup>



## FEATURED OPTICS

DTS Decoder	•
Dolby Digital Decoder	•
Disc Capacity	1
Progressive Scan	•
3:2 Pulldown	•
Playback Formats	DVD-V, DVD-A, SACD-Multi, SACD-Stereo, DVD-R/RW, VCD, CD, CD-R/RW, DivX MP3, WMA, JPEG
Video DAC	108MHz/12-Bit
Audio DAC	192kHz/24-Bit
HDAM	-
Video Circuit Off	•
Display On/Off	•
Power Transformer	EI
Gold Plated Terminals	•
Chassis	Metal
Zero-Impedance Plate	-
Double Layered Bottom Plates	-
Headphone	-
Video Scaler	•
Bass Management	•
Lip Sync. (Digital audio delay)	-
Separate Power Supply for Audio	-

## INPUTS/OUTPUTS

<b>VIDEO</b>	
HDMI Out	1
Component Out	1
S-Video Out	1
Composite Out	1
<b>AUDIO</b>	
Analog Out (RCA)	1
5.1ch Analog Out	1
Optical Digital Out	1
Coaxial Digital Out	1
<b>OTHERS</b>	
External Control (RS232C)	-
D-Bus Remote (RC-5) In/Out	1 / 1

## SPECIFICATIONS

Freq. Response (Digital Audio)	4Hz - 88kHz (DVD-Audio, fs: 192kHz)
S/N Ratio	115 dB
Dynamic Range	100 dB
THD (1kHz)	0.0045%

## GENERAL

Color	Black
Front Panel	Aluminum
Remote Control	Device Remote RC6600DV
Power Requirements	AC120V 60Hz
Power Consumption	20W
Dimensions W x H x D (Inches)	17 <sup>3</sup> / <sub>16</sub> " x 2 <sup>2</sup> / <sub>16</sub> " x 12 <sup>3</sup> / <sub>16</sub> "
Weight (lbs.)	5.5



\*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.