

SA8001

## SUPER AUDIO CD PLAYER



Marantz proudly presents a triumphant achievement: the remarkable SA8001 Super Audio CD player. By incorporating our vast knowledge with the development of the SA-11S1 and SA-15S1 SACD players, Marantz is now able to deliver the depth, dynamics and sonic accuracy at a remarkable new price. Improving on a legendary platform (the SA8260 - five years on Stereophile Magazine's Recommended Components list), the SA8001 will find its way onto every budget minded music lover's wish list.

- Plays Stereo SACD, CD, CD-R/RW
- Current Feedback Circuit with Marantz Original HDAM®
- Cirrus Logic CS4397 DAC with Digital Filter
- Exclusively Designed Original Mechanism for Audio Playback
- Zero Impedance Copper Ground Plate for Analog Terminals
- Double Layered Bottom Chassis
- Audiophile Grade Power Supply Unit with Toroidal Transformer
- Audiophile Grade Selected Components and Terminals
- Quick Replay mode
- High Quality Headphone Circuit
- Super Audio CD Text
- D-BUS (RC-5 In/Out) Remote Connection
- Detachable Power Cord
- Device Remote

## FEATURES

Disc Capacity	1
Multi-ch Capability	-
Playback Formats	SACD-Stereo, CD, CD-R/RW
HDAM	•
Power Transformer	Toroidal
Zero-Impedance Plate	-
Double Layered Bottom Plates	•
Audio DAC	192kHz/24-Bit
Display On/Off	•
Selectable Filters	-
SACD/CD Text	• (SACD)

## IN/OUTPUTS

AUDIO	
Analog L&R Out	1 (Unbalanced)
Analog 5.1ch Out	-
Digital Opt. Out	1
Digital Coax. Out	1
Headphone Out	•
OTHER	
D-Bus Remote (RC-5) In/out	1/1

## GENERAL

Color	Black
Faceplate	Aluminum
Remote	Device Remote RC8001SA
Power Requirement	AC 120V 60Hz
Power Consumption	20W
Dimensions W x H x D (Inches)	17 <sup>5</sup> / <sub>16</sub> " x 5" x 13 <sup>3</sup> / <sub>16</sub> "
Weight (lbs.)	17.6



## SPECIFICATIONS

SACD	
Format	1-Bit DSD
Sampling Frequency	2.8224MHz
Dynamic Range	112 dB
Frequency Response (-3 dB)	2Hz - 50kHz
THD	0.001%
CD AUDIO	
Format	16-Bit Liner PCM
Sampling Frequency	44.1kHz
Dynamic Range	100 dB
Frequency Response	2Hz - 20kHz
THD	0.002%



**marantz®**  
LIFE AMPLIFIED™

\*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.

©2006 Marantz America, Inc. • Marantz America, Inc. • 1100 Maplewood Drive • Itasca, IL 60143 • Phone 630-741-0300 • www.marantz.com