


# MAC7200 stereo receiver

- With 200 Watts per channel, 14 inputs and a high-performance AM/FM tuner, the MAC7200 Stereo Receiver is a music lover's dream.
- Built-in AM/FM tuner will pick up your favorite radio stations with unparalleled clarity and a realism that is free from noise and distortion.
- All digital inputs are housed in the DA1 Digital Audio Module. The DA1 can be replaced by future modules to easily keep the MAC7200 current with all the latest digital audio technologies.
- Supports high resolution digital music up to DSD256 and DXD 384kHz via an 8-channel, 32-bit/192kHz DAC used in Quad Balanced mode.
- Features our new McIntosh Monogrammed Heatsinks™ that are so efficient at dissipating heat that they warrant bearing the McIntosh "Mc" logo.
- Utilizes new, more powerful control microprocessors and some of the latest audio-grade circuit components.
- Full of numerous McIntosh technologies including Autoformers, Power Guard®, Sentry Monitor™, Home Theater PassThru, High Drive headphone amplifier with Headphone Crossfeed Director (HXD®) and Power Control.



A Music Lover's Dream

**McIntosh®**

LEGENDARY PERFORMANCE™

[www.mcintoshlabs.com](http://www.mcintoshlabs.com)

# MAC7200 stereo receiver

## Power Output:

200 Watts per channel. McIntosh Autoformers ensure all speakers receive the full 200 Watts regardless if they are 2, 4 or 8 Ohm impedance.

## Total Harmonic Distortion:

0.005% maximum from 20Hz to 20kHz

## Tone Controls:

Bass and Treble

## Headphone Amplifier:

1/4" High Drive with Headphone Crossfeed Director (HXD®). Powers all headphones from 20 to 600 Ohms.

## Analog Inputs:

5 Unbalanced  
1 Balanced  
1 Moving Coil  
1 Moving Magnet

## Digital Inputs:

2 Coax  
2 Optical  
1 USB  
1 MCT (used with McIntosh MCT series SACD/CD Transports)  
All are housed in DA1 Digital Audio Module.

## Tuner Section:

Features the same AM/FM performance as a stand alone McIntosh tuner. 20 presets available each for band. Includes remote AM antenna for the finest AM reception.

## Home Theater PassThru:

Allows for seamless interfacing with a Home Theater system.

## Overall Dimensions (W x H x D):

17-1/2" (44.5cm) x 7-5/8" (19.37cm) x 22" (55.88cm) including knobs, connectors and cables

## Weight:

75 lbs (34.1kg) net,  
93 lbs (42.3kg) in shipping carton

## For the Consumer's Protection:

In order to ensure the highest level of customer satisfaction, new McIntosh products may only be purchased from an Authorized McIntosh Dealer; and, with certain limited exceptions may only be purchased over-the-counter or delivered and installed by the Authorized McIntosh Dealer. McIntosh does not warrant, in any way, products that are purchased from anyone who is not an Authorized McIntosh Dealer, or that have had their serial numbers altered or defaced.



## Companion Products

The MCD350 SACD/CD Player, MCT450 SACD/CD Transport, MT5 Precision Turntable, MB100 Media Bridge, MB50 Streaming Audio Player and XR50 Bookshelf Loudspeakers are logical companions for the MAC7200 Stereo Receiver. Your Authorized Dealer can provide additional information on other McIntosh product combinations.

To learn more, please call us at 1.800.538.6576.

# McIntosh®

LEGENDARY PERFORMANCE™

www.mcintoshlabs.com