


# MCT450 s a c d / c d t r a n s p o r t

- The MCT450 can be paired with any McIntosh product that contains digital inputs. This includes home theater processors, integrated amplifiers and preamplifiers.
- Digital balanced, coaxial, optical and DIN outputs are available to allow you to connect the MCT450 to a variety of devices. The unique DIN output connects to select McIntosh models with a DIN input for the purest possible sound quality.
- All common disc types are compatible with the MCT450, including SACD, CD, CD-R, and CD-RW. A twin laser optical pickup assures optimal disc reading.
- Premium aluminum die cast CD tray provides the best handling of music discs. 2x read speed for better reading of damaged CDs and CD-R/RWs.
- Power control and data ports simplify operation from other McIntosh system components.



Get the Most from Your CDs

McIntosh®

LEGENDARY PERFORMANCE™

[www.mcintoshlabs.com](http://www.mcintoshlabs.com)

# MCT450 s a c d / c d t r a n s p o r t

## Disc Formats:

SACD, Hybrid SACD, CD, CD-R/RW (MP3 and WMA)

## Digital Audio Outputs:

Coaxial: 0.5V p-p@75ohms  
Optical: -15~-20dBm (TOS Link)  
XLR: 5V p-p@110ohms (AES/EBU)  
DIN: 3V @110ohms

## Digital Audio Outputs Format:

Coaxial: SPDIF, IEC958  
Optical: SPDIF, IEC958  
XLR: SPDIF, IEC958  
DIN: SPDIF, IEC958/DSD (SACD)

## Overall Dimensions (W x H x D):

17-1/2" (44.5cm) x 6" (15.3cm)  
x 19" (48.3cm)

## Weight:

26 lbs (11.8kg) net,  
40.5 lbs (18.4kg) in shipping carton

## Compatible with the following McIntosh models containing digital inputs:

Home Theater Processors:  
MX151, MX150, MX136, MX135, MX134,  
MX132, MX121, MX120, MX119, MHT200,  
MHT100

## Digital Preamps:

D150, D100

## Preamps:

C2500, C50, C48

## Integrated Amps:

MA8000, MA7900, MA6700, MA5200,  
MAC6700, MXA70

## Headphone Amps:

MHA100



## DACS:

MDA1000, MDA700



## For the Consumer's Protection:

In order to ensure the highest level of customer satisfaction, "new" McIntosh products may only be purchased over-the-counter or delivered and installed by an Authorized McIntosh Dealer. McIntosh products that are purchased over the Internet, by phone or mail order are presumed to be "used" and do not qualify for any McIntosh Warranty. McIntosh does not warrant, in any way, products that are purchased from anyone who is not an Authorized Dealer or products that have had their serial number altered or defaced.



## Companion Products

The McIntosh MC452 Amplifier, D150 Digital Preamplifier, MHP1000 Headphones and XR100 Loudspeakers are logical companions for the MCT450 SACD/CD Transport. Your authorized dealer can provide additional information.

To learn more, please call us at 1.800.538.6576.

# McIntosh®

LEGENDARY PERFORMANCE™

www.mcintoshlabs.com