



SQ-N10

The SQ-N10 vacuum tube integrated amplifier is an enhanced version of the SQ-N100 model.

Equipped with the same internal characteristics but now incorporating a dedicated input to accommodate an external docking station, the new SQ-N10 combines functionality and technology with tradition as seen in all Luxman products.

Built with a compact body, the SQ-N10 can be positioned at various locations within a room, and is capable of producing superb sound quality without reduction in utility including the phono input to support a record player, the tone control circuit, and the volume adjustment function with use of the remote control.

SPECIFICATIONS

Item	Value
Continuous power output	12W + 12W (6 Ohms) 10W + 10W (8 Ohms, 4 Ohms)
Input Sensitivity	Line 150mV, Phono (MM) 2.2mV
Input Impedance	47 kOhms
Total Harmonic distortion rate	0.3% or less (1kHz/6Ohms)
Frequency Response	20Hz - 50kHz (-3dB)
S/N Ratio	90dB or more
Vacuum Tube Used	ECC83 x 1, ECC82 x 2, EL84 x 4
Power Consumption	95W (Electrical Appliance and Material Safety Law) 71W (under no signal)
Outside Dimension	297mm (W) x 162mm (H) x 210mm (D) (258mm: connections / controls included)
Weight	11.5kg

